Samsung SGH-a436

(red or Black)

BLUETOOTH® WIRELESS TECHNOLOGY

Connect easily to wireless headsets or other devices featuring Bluetooth Wireless Technology.

INTEGRATED CAMERA

Take and share photographs with family and friends with the a436's digital camera. Want to get closer? You can with its digital zoom.

EDGE GSM QUAD-BAND

Download games,applications, and multimedia messages with EDGE Technology.

Key Features

- HAC Compliant: M3 T4
- Sleek styling
- Large keypad
- Bluetooth for speakerphones and headsets

Specifications:

- Frequency: 850/900/1800/1900 MHz (Quad-Band)
- Dimensions: 3.74" x 1.89" x .63". Weight: 2.90 ounces
- Bluetooth connectivity
- VGA Camera
- Flip design without antenna
- Talk Time: Up to 3 hours. Standby Time: Up to 250 hours

CelleBrite Data Transfer Instructions:

1. Select the proper transfer method. (Phone to Phone, Backup or Restore.)
2. Select "**Samsung GSM**" as the Source or Target "**Vendor**"
3. Select "**A437**" as the Source or Target "**Model**"
4. The Cellebrite cable for data transfer is # **97**
5. Follow normal transfer protocol to transfer, backup or restore data to or from this phone.

Core Accessories:

Car Charger:	$24.95	Part Number:	441981
Home Charger:	$24.95	Part Number:	412908
Cases:	$19.95	Part Number:	350522
Battery:	$59.95	Part Number:	AB533640AABSTD

Optional Accessories:

Bluetooth Headsets:

➡ Plantronics 640e:	$99.99	Part Number:	640e
➡ Plantronics V510:	$79.99	Part Number:	v510
➡ Samsung e200:	$69.99	Part Number:	e200(color)
➡ Sony PV705:	$49.99	Part Number:	PV705
Sony Car Bluetooth:	$99.99	Part Number:	US-093744
Nokia Bluetooth Car Kit:	$179.99	Part Number:	CK-7W
Wilson Car Cradle:	$39.99	Part Number:	301146
Wilson Adapter:	$5.59	Part Number:	RFE-6108
Magnet Antenna:	$47.95	Part Number:	ASPRDM1994T
Install Antenna:	$35.99 + $25.99	Part Number:	ASPDM1965 + KEX166

If you are having a problem with a phone picture messaging or getting on the internet you will need to make sure to delete any previous settings from the phone and then proceed with the OTA. If you OTA a phone without deleting the previous settings the OTA may not work properly and will cause more problems than you previously may have had. Please follow these instructions for deleting the settings in the phone and then OTA the phone.

Deleting WAP and MMS settings from Sony phones:

6. Go to Menu → Internet → Browser Profiles
7. Delete all internet profiles. There are usually UNIONMMS and UNIONWAP internet profiles to be deleted, but there may be many copies of these to delete.
8. Go to Menu → Messaging → Settings → Picture Message → MMS Profile and delete all MMS profiles. There is usually only a UNIONMMS profile to delete, but there could be more.
9. Go to Menu → Messaging→ Settings→ Multimedia Message → Multimedia Message Profile
10. Delete all existing profiles and proceed to OTA the phone.

OTA programming:

1. Open the OTA page by clicking on the link found under the “CC” tab on the UTC intranet page: http://utc/CC.aspx?page=Customer-Care
2. Enter the full phone number in the first space (i.e. “+13071234567”)
3. Click on the “WAP” Settings option and then select the PIN type as “Pin”.
4. Enter an easy to remember four digit number (usually “1111”).
5. Click the “Submit” button and then click “Continue”.
6. Click on the “MMS” Settings selector and click “Submit” and then click “Continue”.
7. The phone will receive the messages and ask if you would like to install.
8. Select “Yes” on the phone and then enter the passcode of “1111”.
9. The phone is now programmed for WAP.
10. The phone will immediately ask if you would like to install for the MMS.
11. Select “Yes” on the phone and then enter the passcode of “1111”.
12. The phone is now programmed for MMS.
13. You should now test to ensure that you can access the internet and send/receive a picture message.

Manual Programming for the Samsung SGH-a436

A. Go to Menu → Internet→ Browser Profiles

1. Select Profile Settings→ Profile 1

a. Set Profile Name = WAP

b. Set Home URL = http://menu.unioncell.info

c. Check Proxy

d. Set IP Address = 166.230.4.83

e. Set Proxy Port = 8799

f. Set Bearer = GPRS

g. Select Advanced Settings

1. Set APN = union.wap.com
2. Select Save

h. Select Save

2. Select Profile Settings and highlight WAP. Select Options and Activate.

B. Go to Menu → Messaging→ Settings→ Multimedia Message → Multimedia Message Profile

1. Select Profile 2

a. Set Profile Name = MMS

b. Set Server URL = http://mmsc/01

c. Check Proxy

d. Select IPAddress = 166.230.4.83

e. Port 8799

f. Select Bearer = GPRS

g. Select Advanced Settings

1. Set APN = union.mms.com
2. Select Save

h. Select Save

1. Set Proxy Address = 166.230.4.83
2. Set Proxy Port = 8799
2. Set APN = union.mms.com

3. Highlight MMS. Select Options→Activate.